
Three-phase reactors for harmonic filtering at the converter output with bimetal overtemperature protection, finished with resin and anti-flash varnished.




## **Technical characteristics**

| Rated current           | 160 A                      |
|-------------------------|----------------------------|
| Motor rating            | 75 kW / 100 CV             |
| Line voltage            | 380 - 460 V                |
| Reactor                 | 0,138 mH (50 Hz)           |
| Voltage drop            | 3% (50 Hz)                 |
| Thermal overload factor | 0,05                       |
| Frequency               | 50/60 Hz                   |
| Protection degree       | IP-00                      |
| Cooling                 | AN                         |
| Ambient temperature     | 45 ºC                      |
| Temperature rise        | Class F - 155≌C            |
| Insulation              | Clase H - 180 ºC           |
| Windings                | Class HC - 200 ºC          |
| Test voltage            | 3 kV (1 min, 50 Hz)        |
| Standards               | IEC/EN/UNE-EN 60076-6, CE  |
| Mounting                | Screws                     |
| Includes                | Bimetal thermal protection |
| Weight                  | 38,7 kg                    |
|                         |                            |

# Electric scheme



## Dimensions



Dimensions (AxBxCxDxE): 340x219x375x120x310 mm 10Ø

# RTOX160 | RTOX THREE-PH

Three-phase reactors for harmonic filtering at the converter output with bimetal overtemperature protection, finished with resin and anti-flash varnished.

### Features

#### Reactor

Anti-flash varnish finish, offering:

- Protection against corrosive environments
- Increase of electrical isolation
- High compression capacity
- Reduction of noise level
- Increase of product's lifespan

#### Safety class I

Includes thermal protection against overtemperatures Possibility of tailor-made manufacturing Technical remarks about the use of line reactors:

- Attenuation of voltage peaks in the output of the converter, protecting against premature degradation of the dielectrical parts of the motor
- Reduction of the reflection effect due to the length of the cables between the converter and the motor. This effect amplifies voltage values in the terminals of the motor
- It is recomended to use these inductances for lengths over 50 m from the converter to the motor

### Downloads